



. . . c o n n e c t i n g y o u r b u s i n e s s

LANCOM 1821n Wireless

VPN router with ADSL2+ modem and performance WLAN module

- Integrated ADSL2+ modem
- 5 integrated IPsec VPN channels, upgradable to 25, integrated hardware acceleration
- 300-Mbps WLAN as per 802.11a/b/g/n
- Secure WLAN compliant with IEEE 802.11i (WPA2/ AES) and Multi-SSID
- Stateful-inspection firewall with intrusion detection/denial-of-service protection
- Multiple interfaces: ISDN, USB-2.0 port, Ethernet, and serial port

The LANCOM 1821n Wireless provides everything you need for site connectivity: Offering 5 integrated VPN channels, which can be upgraded to 25 by means of a VPN option, it comes with an on-board ADSL2+ modem. The device connects directly to the Internet—no additional modem is required. A range of interfaces, including ISDN, four separable switch ports, serial port and USB-2.0 port, facilitate the connection to PBX systems and network devices; should the device be unattainable via IP, it provides alternative access to the configuration. Load balancing can use up to four WAN connections. Security is provided by high-quality security features such as the stateful-inspection firewall with intrusion detection and protection against denial of services.

And there's more: The new WLAN module works at 300 Mbps and achieves far greater ranges than the product's predecessor. The hugely improved coverage from the integrated MIMO technology allows entire offices to be networked, without requiring additional access points. Multi-SSID enables the definition of multiple user groups, which makes it simple to set up WLAN access for guests, who remain completely separated from the company's internal network.

More Security.

The integrated firewall with the up-to-date security functions such as stateful inspection, intrusion detection and denial-of-service protection is supplemented by dynamic bandwidth management and comprehensive backup functions, high availability and redundancy over ISDN and VRRP. The integrated VPN gateway meets the IPsec standard, supporting high-security 3-DES or AES encryption. In combination with digital-certificate support and integrated hardware accelerator, optimal security is assured for connections to telecommuters and branch offices. LANCOM also sets standards in the area of wireless LAN security. Our products support a comprehensive range of WLAN security technologies, including IEEE 802.11i (WPA2/AES), 802.1x, WEP64/128/152, ACL or LEPS (LANCOM Enhanced Passphrase Security). Whatever your individual security requirements may be, you can configure your own made-to-measure solution.

More Management.

The free tool WLANmonitor allows settings for wireless, encryption, or access-control lists to be grouped into partial configurations, which are then transferred to multiple access points in one easy move. WLANmonitor visualizes the structures of the wireless LAN irrespective of physical location and helps with the central monitoring of the entire wireless network. LANCOM WLAN controllers provide the ultimate in management: Every LANCOM access point and LANCOM WLAN router, including those at remote locations, can be remotely configured via VPN from a central site. The practical significance of this becomes clear when rolling-out new WLAN infrastructure.

The WLAN devices merely have to be connected to a network with IP access. Configuration is carried out centrally via the Controller. The benefit: WLANs can be rolled-out at locations where no trained technician is available.

More Reliability for the Future.

From the earliest days, LANCOM products have been designed for a product life of several years. They are equipped with hardware which is dimensioned for the future. Even reaching back to older product generations, updates to the LANCOM Operating System—LCOS—are available several times a year, free of charge and offering major features. LANCOM offers unbeatable protection of your investment!

More Virtualization.

The versatile functions for address translation and routing allow completely different networks to be connected over common infrastructure. Existing networks at partner companies, home-office workstations or subsidiaries can be integrated into the VPN without problem. This is our understanding of network virtualization.

LANCOM 1821n Wireless

Scope of features: as of LCOS version 7.8x

| WLAN | |
|--|--|
| Frequency band 2.4 GHz or 5 GHz | 2400-2483.5 MHz (ISM) or 5150-5825 MHz (depending on country-specific restrictions) |
| Data rates 802.11b/g | 54 Mbps to IEEE 802.11g (fallback to 48, 36, 24, 18, 12, 9, 6 Mbps, Automatic Rate Selection) compatible to IEEE 802.11b (11, 5.5, 2, 1 Mbps, Automatic Rate Selection), 802.11 b/g compatibility mode or pure g or pure b |
| Data rates 802.11a/h | 54 Mbps (fallback to 48, 36, 24, 18, 12, 9, 6 Mbps, Automatic Rate Selection), fully compatible with TPC (adjustable power output) and DFS 2 (automatic channel selection, radar detection) according to ETSI regulations. |
| Data rates 802.11n | 300 Mbps according to IEEE 802.11n with MCS15 (Fallback to 6,5 Mbps with MCS0) |
| Range 802.11a/b/g * | Up to 150 m (up to 30 m in buildings) * |
| Range 802.11n | Up to 250 m @ 6.5 Mbps (up to 20 m @ 300 Mbps indoor)* |
| Output power at antenna connector, 2.4 GHz | 802.11b: +19 dBm @ 1 and 2 Mbps, +19 dBm @ 5.5 und 11 Mbps |
| Output power at antenna connector, 2.4 GHz | 802.11g: +18 dBm @ 6 to 36 Mbps, +17 dBm @ 48 Mbps, +16 dBm @ 54 Mbps 802.11n: +19 dBm @ 6,5/13 Mbps (MCS0/8, 20 MHz), +10 dBm @ 65/130 Mbps (MCS7/15, 20 MHz), +17 dBm @ 15/30 Mbps (MCS0/8, 40 MHz), +10 dBm @ 150/300 Mbps (MCS7/15, 40 MHz) |
| Output power at antenna connector, 5 GHz | 802.11a/h: +18 dBm @ 6 to 24 Mbps, +17 dBm @ 36 Mbps, +16 dBm @ 48 Mbps, +15 dBm @ 54 Mbps 802.11n: +18 dBm @ 6,5/13 Mbps (MCS0/8, 20 MHz), +10 dBm @ 65/130 Mbps (MCS7/15, 20 MHz), +17 dBm @ 15/30 Mbps (MCS0/8, 40 MHz), +10 dBm @ 150/300 Mbps (MCS7/15, 40 MHz) |
| Max. radiated power (EIRP), 2.4 GHz band | 802.11b/g: Up to 20 dBm / 100 mW EIRP (transmission power control according to TPC or manual settings) |
| Max. radiated power (EIRP), 5 GHz band | 802.11a/h: Up to 30 dBm / 1000 mW or up to 36 dBm / 4000 mW EIRP (depending on national regulation on channel usage and subject to further obligations such as TPC and DFS) |
| Minimum transmission power | Transmission power reduction in software in 1 dB steps to min. 0.5 dBm |
| Receiver sensitivity 2.4 GHz | 802.11b: -91 dBm @ 11 Mbps, -96 dBm @ 1 Mbps; *802.11g: -96 dBm @ 6 Mbps, -83 dBm @ 54 Mbps; 802.11n: -96 dBm @ 6,5 Mbps (MCS0, 20 MHz), -79 dBm @ 65 Mbps (MCS7, 20 MHz); -95 dBm @ 13 Mbps (MCS8, 20 MHz), -75 dBm @ 130 Mbps (MCS15, 20 MHz); -90 dBm @ 15 Mbps (MCS0, 40 MHz), -75 dBm @ 150 Mbps (MCS7, 40 MHz); -90 dBm @ 30 Mbps (MCS8, 40 MHz), -71 dBm @ 300 Mbps (MCS15, 40 MHz) |
| Receiver sensitivity 5 GHz | 802.11a/h: -95 dBm @ 6 Mbps, -82 dBm @ 54 Mbps; 802.11n: -95 dBm @ 6,5 Mbps (MCS0, 20 MHz), -77 dBm @ 65 Mbps (MCS7, 20 MHz); -94 dBm @ 13 Mbps (MCS8, 20 MHz), -74 dBm @ 130 Mbps (MCS15, 20 MHz); -91 dBm @ 15 Mbps (MCS0, 40 MHz), -74 dBm @ 150 Mbps (MCS7, 40 MHz); -91 dBm @ 30 Mbps (MCS8, 40 MHz), -70 dBm @ 300 Mbps (MCS15, 40 MHz) |
| Radio channels 2.4 GHz | Up to 13 channels, max. 3 non-overlapping (2.4 GHz band) |
| Radio channels 5 GHz | Up to 26 non-overlapping channels (available channels and further obligations such as automatic DFS2 dynamic channel selection depending on national regulation) |
| Roaming | Seamless handover between radio cells, IAPP support with optional restriction to an ARF context, IEEE 802.11d support |
| WPA2 fast roaming | Pre-authentication and PMK caching for fast roaming |
| Fast client roaming | With background scanning, moving LANCOM 'client mode' access points pre-authenticate to alternative access points which offer a better signal before Roaming fails |
| VLAN | VLAN ID definable per interface, WLAN SSID, point-to-point connection and routing context (4094 IDs) |
| Dynamic VLAN assignment | Dynamic VLAN assignment for target user groups based on MAC addresses, BSSID or SSID by means of external RADIUS server. |
| Q-in-Q tagging | Support of layered 802.1q VLANs (double tagging) |
| Multi-SSID | Simultaneous use of up to 8 independent WLAN networks per WLAN interface |
| IGMP snooping | Support for Internet Group Management Protocol (IGMP) in the WLAN bridge for WLAN SSIDs and LAN interfaces for specific switching of multicast packets (devices with integrated WLAN only). Automated detection of multicast groups. Configurable action for multicast packets without registration. Configuration of static multicast group members per VLAN ID. Configuration of query simulation for multicast membership per VLAN ID |
| Security | IEEE 802.11i / WPA2 with passphrase or 802.1x and hardware-accelerated AES, closed network, WEP64, WEP128, WEP152, user authentication, 802.1x /EAP, LEPS, WPA1/TKIP |
| RADIUS server | Integrated RADIUS server for MAC address list management |
| EAP server | Integrated EAP server for authentication of 802.1x clients via EAP-TLS, EAP-TTLS, PEAP, MSCHAP or MSCHAPv2 |
| Quality of Service | Prioritization according to Wireless Multimedia Extensions (WME, subset of IEEE 802.11e) |
| U-APSD/WMM Power Save | Extension of power saving according to IEEE 802.11e by Unscheduled Automatic Power Save Delivery (equivalent to WMM Power Save). U-APSD supports the automatic switch of clients to a doze mode. Increased battery lifetime for telephone calls over VoWLAN (Voice over WLAN) |
| Bandwidth limitation | Maximum transmit and receive rates and an individual VLAN ID can be assigned to each WLAN client (MAC address) |
| Background scanning | Detection of rogue AP's and the channel information for all WLAN channels during normal AP operation. The Background Scan Time Interval defines the time slots in which an AP or Router searches for a foreign WLAN network in its vicinity. The time interval can be specified in either milliseconds, seconds, minutes, hours or days |

| WLAN | |
|---|--|
| Client detection | Rogue WLAN client detection based on probe requests |
| 802.1x supplicant | Authentication of an access point in WLAN client mode at another access point via 802.1x (EAP-TLS, EAP-TTLS and PEAP) |
| *) Note | The effective distances and transmission rates that can be achieved are depending of the site RF conditions |
| IEEE 802.11n Features | |
| MIMO | MIMO technology is a technique which uses multiple transmitters to deliver multiple data streams via different spatial channels. LANCOM uses a 3 x 3 MIMO Configuration where 2 data streams are spread over 3 transmitters. Depending on the existing RF conditions the throughput is doubled with MIMO technology |
| 40 MHz Channels | Two adjacent 20 MHz channels are combined to create a single 40 MHz channel. Depending on the existing RF Conditions channel bonding doubles the throughput. |
| MAC Aggregation and Block Acknowledgement | MAC Aggregation increase the 802.11 MAC efficiency by combining MAC data frames and sending it out with a single header. The receiver acknowledges the combined MAC frame with a Block Acknowledgement. Depending on existing RF conditions, this technique improves throughput by up to 20%. |
| Short Guard Interval | The guard interval is the time between OFDM symbols in the air. 802.11n gives the option for a shorter 400 nsec guard interval compared to the legacy 800 nsec guard interval. Under ideal RF conditions this increases the throughput by upto 10% |
| BFWA* | Support for Broadband Fixed Wireless Access in 5.8 GHz band with up to 4 Watts transmitter power for WLAN point-to-point links according to the national regulations of your country, special antennas required |
| *) Note | The use of BFWA is subject to country specific regulation |
| WLAN operating modes | |
| WLAN access point | Infrastructure mode (autonomous operation or managed by LANCOM WLAN Controller) |
| WLAN bridge | Point-to-multipoint connection of up to 7 Ethernet LANs (mixed operation optional), broken link detection, blind mode, supports VLAN When configuring Pt-to-Pt links, pre-configured names can be used as an alternative to MAC Adresses for creating a link. Rapid spanning-tree protocol to support redundant routes in Ethernet networks |
| WLAN client | Transparent WLAN client mode for wireless Ethernet extensions, e.g. connecting PCs or printers by Ethernet; up to 64 MAC addresses. Automatic selection of a WLAN profile (max. 8) with individual access parameters depending on signal strength or priority |
| Firewall | |
| Stateful inspection firewall | Incoming/Outgoing Traffic inspection based on connection information. Trigger for firewall rules depending on backup status, e.g. simplified rule sets for low-bandwidth backup lines. Limitation of the number of sessions per remote site (ID) |
| Packet filter | Check based on the header information of an IP packet (IP or MAC source/destination addresses; source/destination ports, DiffServ attribute); remote-site dependant, direction dependant, bandwidth dependant |
| Extended port forwarding | Network Address Translation (NAT) based on protocol and WAN address, i.e. to make internal webservers accessible from WAN |
| N:N IP address mapping | N:N IP address mapping for translation of IP addresses or entire networks |
| Tagging | The firewall marks packets with routing tags, e.g. for policy-based routing |
| Actions | Forward, drop, reject, block sender address, close destination port, disconnect |
| Notification | Via e-mail, SYSLOG or SNMP trap |
| Quality of Service | |
| Traffic shaping | Dynamic bandwidth management with IP traffic shaping |
| Bandwidth reservation | Dynamic reservation of minimum and maximum bandwidths, totally or connection based, separate settings for send and receive directions. Setting relative bandwidth limits for QoS in percent |
| DiffServ/TOS | Priority queuing of packets based on DiffServ/TOS fields |
| Packet-size control | Automatic packet-size control by fragmentation or Path Maximum Transmission Unit (PMTU) adjustment |
| Layer 2/Layer 3 tagging | Automatic or fixed translation of layer-2 priority information (802.11p-marked Ethernet frames) to layer-3 DiffServ attributes in routing mode. Translation from layer 3 to layer 2 with automatic recognition of 802.11p-support in the destination device |
| Security | |
| Intrusion Prevention | Monitoring and blocking of login attempts and port scans |
| IP spoofing | Source IP address check on all interfaces: only IP addresses belonging to the defined IP networks are allowed |
| Access control lists | Filtering of IP or MAC addresses and preset protocols for configuration access and LANCAPI |
| Denial of Service protection | Protection from fragmentation errors and SYN flooding |
| General | Detailed settings for handling reassembly, PING, stealth mode and AUTH port |
| URL blocker | Filtering of unwanted URLs based on DNS hitlists and wildcard filters |
| Password protection | Password-protected configuration access can be set for each interface |
| Alerts | Alerts via e-mail, SNMP-Traps and SYSLOG |

| Security | |
|------------------------------------|---|
| Authentication mechanisms | EAP-TLS, EAP-TTLS, PEAP, MS-CHAP, MS-CHAPv2 as EAP authentication mechanisms, PAP, CHAP, MS-CHAP and MS-CHAPv2 as PPP authentication mechanisms |
| Anti-theft | Anti-theft ISDN site verification over B or D channel (self-initiated call back and blocking) |
| WLAN protocol filters | Limitation of the allowed transfer protocols, source and target addresses on the WLAN interface |
| Adjustable reset button | Adjustable reset button for 'ignore', 'boot-only' and 'reset-or-boot' |
| IP redirect | Fixed redirection of any packet received over the WLAN interface to a dedicated target address |
| High availability / redundancy | |
| VRRP | VRRP (Virtual Router Redundancy Protocol) for backup in case of failure of a device or remote station. Enables passive standby groups or reciprocal backup between multiple active devices including load balancing and user definable backup priorities |
| FirmSafe | For completely safe software upgrades thanks to two stored firmware versions, incl. test mode for firmware updates |
| ISDN backup | In case of failure of the main connection, a backup connection is established over ISDN. Automatic return to the main connection |
| Analog/GSM modem backup | Optional operation of an analog or GSM modem at the serial interface |
| Load balancing | Static and dynamic load balancing over up to 4 WAN connections. Channel bundling with Multilink PPP (if supported by network operator) |
| VPN redundancy | Backup of VPN connections across different hierarchy levels, e.g. in case of failure of a central VPN concentrator and re-routing to multiple distributed remote sites. Any number of VPN remote sites can be defined (the tunnel limit applies only to active connections). Up to 32 alternative remote stations, each with its own routing tag, can be defined per VPN connection. Automatic selection may be sequential, or dependant on the last connection, or random (VPN load balancing) |
| Line monitoring | Line monitoring with LCP echo monitoring, dead-peer detection and up to 4 addresses for end-to-end monitoring with ICMP polling |
| VPN | |
| Number of VPN tunnels | 5 IPsec connections active simultaneously (25 with VPN-25 Option), unlimited configurable connections. Configuration of all remote sites via one configuration entry when using the RAS user template or Proadaptive VPN. Max. total sum of concurrently active IPsec and PPTP tunnels: 5 (25 with VPN 25 Option) |
| Hardware accelerator | Integrated hardware accelerator for 3DES/AES encryption and decryption |
| 1-Click-VPN Client assistant | One click function in LANconfig to create VPN client connections, incl. automatic profile creation for the LANCOM Advanced VPN Client |
| 1-Click-VPN Site-to-Site | Creation of VPN connections between LANCOM routers via drag and drop in LANconfig |
| IKE | IPsec key exchange with Preshared Key or certificate |
| Certificates | X.509 digital multi-level certificate support, compatible with Microsoft Server / Enterprise Server and OpenSSL, upload of PKCS#12 files via HTTPS interface and LANconfig. Simultaneous support of multiple certification authorities with the management of up to nine parallel certificate hierarchies as containers (VPN-1 to VPN-9). Simplified addressing of individual certificates by the hierarchy's container name (VPN-1 to VPN-9). Wildcards for certificate checks of parts of the identity in the subject. Secure Key Storage protects a private key (PKCS#12) from theft |
| Certificate rollout | Automatic creation, rollout and renewal of certificates via SCEP (Simple Certificate Enrollment Protocol) per certificate hierarchy |
| Certificate revocation lists (CRL) | CRL retrieval via HTTP per certificate hierarchy |
| XAUTH | XAUTH client for registering LANCOM routers and access points at XAUTH servers incl. IKE-config mode. XAUTH server enables clients to register via XAUTH at LANCOM routers. Connection of the XAUTH server to RADIUS servers provides the central authentication of VPN-access with user name and password. Authentication of VPN-client access via XAUTH and RADIUS connection additionally by OTP token |
| RAS user template | Configuration of all VPN client connections in IKE ConfigMode via a single configuration entry |
| Proadaptive VPN | Automated configuration and dynamic creation of all necessary VPN and routing entries based on a default entry for site-to-site connections. Propagation of dynamically learned routes via RIPv2 if required |
| Algorithms | 3DES (168 bit), AES (128, 192 or 256 bit), Blowfish (128 bit), RSA (128 or -448 bit) and CAST (128 bit). OpenSSL implementation with FIPS-140 certified algorithms. MD-5 or SHA-1 hashes |
| NAT-Traversal | NAT-Traversal (NAT-T) support for VPN over routes without VPN passthrough |
| IPCOMP | VPN data compression based on LZS or Deflate compression for higher IPsec throughput |
| LANCOM Dynamic VPN | Enables VPN connections from or to dynamic IP addresses. The IP address is communicated via ISDN B- or D-channel or with the ICMP or UDP protocol in encrypted form. Dynamic dial-in for remote sites via connection template |
| Dynamic DNS | Enables the registration of IP addresses with a Dynamic DNS provider in the case that fixed IP addresses are not used for the VPN connection |
| Specific DNS forwarding | DNS forwarding according to DNS domain, e.g. internal names are translated by proprietary DNS servers in the VPN. External names are translated by Internet DNS servers |
| VPN throughput (max., AES) | |
| 1416-byte frame size UDP | 46 Mbps |
| 256-byte frame size UDP | 8 Mbps |
| IMIX | 14 Mbps |

| | |
|-----------------------------------|--|
| Firewall throughput (max.) | |
| 1518-byte frame size UDP | 65 Mbps |
| 256-byte frame size UDP | 17 Mbps |
| Routing functions | |
| Router | IP and NetBIOS/IP multi-protocol router |
| ARP lookup | Packets sent in response to LCOS service requests (e.g. for Telnet, SSH, SNMP, SMTP, HTTP(S), SNMP, etc.) via Ethernet can be routed directly to the requesting station (default) or to a target determined by ARP lookup |
| Advanced Routing and Forwarding | Separate processing of 16 contexts due to virtualization of the routers. Mapping to VLANs and complete independent management and configuration of IP networks in the device, i.e. individual settings for DHCP, DNS, Firewalling, QoS, VLAN, Routing etc. Automatic learning of routing tags for ARF contexts from the routing table |
| HTTP | HTTP and HTTPS server for configuration by web interface |
| DNS | DNS client, DNS server, DNS relay, DNS proxy and dynamic DNS client |
| DHCP | DHCP client, DHCP relay and DHCP server with autodetection. Cluster of several LANCOM DHCP servers per context (ARF network) enables caching of all DNS assignments at each router |
| NetBIOS | NetBIOS/IP proxy |
| NTP | NTP client and SNTP server, automatic adjustment for daylight-saving time |
| Policy-based routing | Policy-based routing based on routing tags. Based on firewall rules, certain data types are marked for specific routing, e.g. to particular remote sites or lines |
| Dynamic routing | Dynamic routing with RIPv2. Learning and propagating routes; separate settings for LAN and WAN. Extended RIPv2 including HopCount, Poisoned Reverse, Triggered Update for LAN (acc. to RFC 2453) and WAN (acc. to RFC 2091) as well as filter options for propagation of routes. Definition of RIP sources with wildcards |
| COM port server | |
| COM port forwarding | COM-port server for DIN and USB interfaces. For multiple serial devices connected to it, the server also manages its own virtual COM ports via Telnet (RFC 2217) for remote maintenance (works with popular virtual COM-port drivers compliant with RFC 2217). Switchable newline conversion and alternative binary mode. TCP keepalive according to RFC 1122 with configurable keepalive interval, retransmission timeout and retries |
| USB print server | |
| Print server (USB 2.0) | Host port for connecting USB printers via RAW-IP and LPD; bi-directional data exchange is possible |
| LAN protocols | |
| IP | ARP, proxy ARP, BOOTP, LANCAP, DHCP, DNS, HTTP, HTTPS, IP, ICMP, NTP/SNTP, NetBIOS, PPPoE (server), RADIUS, RIP-1, RIP-2, RTP, SIP, SNMP, TCP, TFTP, UDP, VRRP |
| Rapid Spanning Tree | 802.1d Spanning Tree and 802.1w Rapid Spanning Tree support for dynamic path selection with redundant layer 2 connections |
| WAN protocols | |
| ADSL, Ethernet | PPPoE, PPPoA, IPoA, Multi-PPPoE, ML-PPP, PPTP (PAC or PNS) and plain Ethernet (with or without DHCP), RIP-1, RIP-2, VLAN |
| ISDN | 1TR6, DSS1 (Euro-ISDN), PPP, X75, HDLC, ML-PPP, V.110/GSM/HSCSD, CAPI 2.0 via LANCAP, Stac data compression |
| Interfaces | |
| WAN: ADSL | ADSL over ISDN compliant with ITU G.992.1 Annex B (compatible to Deutsche Telekom U-R2 connections) or ADSL over POTS compliant with ITU G.992.1 Annex A |
| WAN: ADSL2+ | ADSL2+ over ISDN compliant with ITU G.992.3, ITU G.992.5 Annex B (ADSL2+) or ADSL2+ over POTS compliant with ITU G.992.3 and ITU G.992.5 Annex A (ADSL2+) |
| Ethernet ports | 4 individual 10/100-Mbps Fast Ethernet ports; up to 3 ports can be switched as additional WAN ports with load balancing. Ethernet ports can be electrically disabled within LCOS configuration |
| - freely configurable | Each Ethernet port can be freely configured (LAN, DMZ, WAN, monitor port, off). LAN ports can be operated as a switch or separately. Additionally, external DSL modems or termination routers can be operated as a WAN port with load balancing and policy-based routing. DMZ ports can be operated with their own IP address range without NAT |
| USB 2.0 host port | USB 2.0 full-speed host port for connecting USB printers (USB print server) or serial devices (COM port server); bi-directional data exchange is possible (max. 12 Mbps) |
| ISDN | ISDN BRI port (S0 bus) |
| Serial interface | Serial configuration interface / COM port (8 pin Mini-DIN): 9,600 - 115,000 baud, suitable for optional connection of analog/GPRS modems |
| External antenna connectors | Two reverse SMA connectors for external LANCOM AirLancer Extender antennas or for antennas from other vendors. Please respect the restrictions which apply in your country when setting up an antenna system. For information about calculating the correct antenna setup, please refer to www.lancom-systems.com |

| Management | |
|---|---|
| LANconfig | Configuration program for Microsoft Windows, incl. convenient Setup Wizards. Optional group configuration, simultaneous remote configuration and management of multiple devices over ISDN dial-in or IP connection (HTTPS, HTTP, TFTP). Configuration program properties per project or user. Automatic storage of the current configuration before firmware updates. Exchange of configuration files between similar devices, e.g. for migrating existing configurations to new LANCOM products. Detection and display of the LANCOM managed switches |
| LANmonitor | Monitoring application for Microsoft Windows for (remote) surveillance and logging of the status of LANCOM devices and connections, incl. PING diagnosis and TRACE with filters and save to file. Search function within TRACE tasks. Wizards for standard diagnostics. Export of diagnostic files for support purposes (including bootlog, sysinfo and device configuration without passwords). Graphic display of key values (marked with an icon in LANmonitor view) over time as well as table for minimum, maximum and average in a separate window, e. g. for Rx, Tx, CPU load, free memory. Monitoring of the LANCOM managed switches |
| WLANmonitor | Monitoring application for Microsoft Windows for the visualization and monitoring of LANCOM WLAN installations, incl. Rogue AP and Rogue Client visualization |
| Firewall GUI | Graphical user interface for configuring the object-oriented firewall in LANconfig: Tabular presentation with symbols for rapid understanding of objects, choice of symbols for objects, objects for actions/Quality of Service/remote sites/services, default objects for common scenarios, individual object definition (e.g. for user groups) |
| WEBconfig | Integrated web server for the configuration of LANCOM devices via Internet browsers with HTTPS or HTTP. Similar to LANconfig with a system overview, syslog and events display, symbols in the menu tree, quick access with side tabs. WEBconfig also features Wizards for basic configuration, security, Internet access, LAN-LAN coupling. Online help for parameters in LCOS menu tree |
| Device Syslog | Syslog buffer in the RAM (size depending on device memory) to store events for diagnosis. Default set of rules for the event protocol in Syslog. The rules can be modified by the administrator. Display and saving of internal Syslog buffer (events) from LANCOM devices with LANmonitor, display only with WEBconfig |
| Access rights | Individual access and function rights for up to 16 administrators |
| User administration | RADIUS user administration for dial-in access (PPP/PPTP and ISDN CLIP). Support for RADSEC (Secure RADIUS) for secure communication with RADIUS servers. |
| Remote maintenance | Remote configuration with Telnet/SSL, SSH (with password or public key), browser (HTTP/HTTPS), TFTP or SNMP, firmware upload via HTTP/HTTPS or TFTP |
| TACACS+ | Support of TACACS+ protocol for authentication, authorization and accounting (AAA) with reliable connections and encrypted payload. Authentication and authorization are separated completely. LANCOM access rights are converted to TACACS+ levels. With TACACS+ access can be granted per parameter, path, command or functionality for LANconfig, WEBconfig or Telnet/SSH. Each access and all changes of configuration are logged. Access verification and logging of SNMP Get and Set requests. WEBconfig supports the access rights of TACACS+ and choice of TACACS+ server at login. LANconfig provides a device login with the TACACS+ request conveyed by the addressed device. Authorization to execute scripts and each command within them by checking the TACACS+ server's database. CRON, action-table and script processing can be diverted to avoid TACACS+ to relieve TACACS+ servers. Redundancy by setting several alternative TACACS+ servers. Configurable option to fall back to local user accounts in case of connection drops to the TACACS+ servers. Compatibility mode to support several free TACACS+ implementations |
| Remote maintenance of 3rd party devices | A remote configuration for devices behind der LANCOM can be accomplished (after authentication) via tunneling of arbitrary TCP-based protocols, e.g. for HTTP(S) remote maintenance of VoIP phones or printers of the LAN |
| ISDN remote maintenance | Remote maintenance over ISDN dial-in with calling-number check |
| TFTP & HTTP(S) client | For downloading firmware and configuration files from a TFTP, HTTP or HTTPS server with variable file names (wildcards for name, MAC/IP address, serial number), e.g. for roll-out management. Commands for live Telnet session, scripts or CRON jobs |
| Security | Access rights (read/write) over WAN or (W)LAN can be set up separately (Telnet/SSL, SSH, SNMP, HTTPS/HTTP), access control list |
| Scripting | Scripting function for batch-programming of all command-line parameters and for transferring (partial) configurations, irrespective of software versions and device types, incl. test mode for parameter changes. Utilization of timed control (CRON) or connection establishment and termination to run scripts for automation. Scripts can send e-mails with various command line outputs as attachments |
| SNMP | SNMP management via SNMP V2, private MIB exportable by WEBconfig, MIB II |
| Timed control | Scheduled control of parameters and actions with CRON service |
| Diagnosis | Extensive LOG and TRACE options, PING and TRACEROUTE for checking connections, LANmonitor status display, internal logging buffer for SYSLOG and firewall events, monitor mode for Ethernet ports |
| LANCOM WLAN Controller | Supported by all LANCOM WLAN Controller (separate optional hardware equipment for installation, optimization, operating and monitoring of WLAN networks, except for P2P connections) |
| LANCAPI | Available for all LANCOM routers with integrated ISDN interface. LANCAPI provides CAPI 2.0 features for Microsoft Windows to utilize ISDN channels over the IP network |
| CAPI Faxmodem | Softmodem for Microsoft Windows that makes use of LANCAPI to send and receive faxes via ISDN |
| Statistics | |
| Statistics | Extensive Ethernet, IP and DNS statistics; SYSLOG error counter |
| Accounting | Connection time, online time, transfer volumes per station. Snapshot function for regular read-out of values at the end of a billing period. Timed (CRON) command to reset all counters at once |
| Export | Accounting information exportable via LANmonitor and SYSLOG |

LANCOM 1821n Wireless

Scope of features: as of LCOS version 7.8x

| | |
|-----------------------------------|---|
| Hardware | |
| Power supply | 12 V DC, external power adapter (230 V) |
| Environment | Temperature range 5–35°C; humidity 0–80%; non-condensing |
| Housing | Robust synthetic housing, rear connectors, ready for wall mounting, Kensington lock; 210 x 45 x 140 mm (W x H x D) |
| Fans | None; fanless design without rotating parts, high MTBF |
| Power consumption (max) | ca. 12 Watts |
| Declarations of conformity | |
| CE | EN 301 489-1, EN 301 489-17, EN 60950 |
| 2.4 GHz WLAN | ETS 300 328 |
| 5 GHz WLAN | EN 301 893 version 1.4.1 (incl. DFS 2) |
| Notifications | Certifications notified in Germany, Belgium, Netherlands, Luxembourg, Austria, Switzerland, UK, Italy, Spain, France, Portugal, Czech Republic, Denmark, Malta |
| Package content | |
| Manual | Printed User Manual (DE, EN) and Quick Installation Guide (DE/EN/FR/ES/IT/PT/NL) |
| CD | CD with firmware, management software (LANconfig, LANmonitor, WLANmonitor, LANCAPI) and documentation |
| Cable | Serial configuration cable, 1.5m |
| Cable | 1 Ethernet cable, 3m |
| Cable | ADSL cable, 3m |
| Cable | ISDN cable, 3m |
| Antennas | Two 3 dBi external dipole dualband antennas, one internal 3dBi dipole dualband antenna |
| Power supply unit | 12 V DC, external power adapter (230 V) |
| Support | |
| Warranty | 3 years Support via Hotline and Internet KnowledgeBase |
| Software updates | Regular free updates (LCOS operating system and management tools) via Internet |
| Options | |
| VPN | LANCOM VPN-25 Option (25 channels), item no. 60083 |
| Advance Replacement | LANCOM Next Business Day Service Extension CPE, item no. 61411 |
| Warranty Extension | LANCOM 2-Year Warranty Extension CPE, item no. 61414 |
| Public Spot | LANCOM Public Spot Option (authentication and accounting software for hotspots, incl. Voucher printing through Standard PC printer), Item no. 60642. |
| Fax Gateway | LANCOM Fax Gateway Option activates 'hardfax' within the router. Supports 2 parallel fax channels with LANCAPI ('fax group 3' without use of CAPI Faxmodem), item no. 61425 |
| Accessories | |
| LANCOM WLC-4006 | LANCOM WLAN Controller for central management of 6 or 12 LANCOM access points and WLAN routers, item no. 61367 |
| LANCOM WLC-4006 (UK) | LANCOM WLAN Controller for central management of 6 or 12 LANCOM access points and WLAN routers, item no. 61368 for UK |
| LANCOM WLC-4025+ | LANCOM WLAN Controller for central management of 25, 50 or 100 LANCOM access points and WLAN routers, item no. 61378 |
| LANCOM WLC-4025+ (UK) | LANCOM WLAN Controller for central management of 25, 50 or 100 LANCOM access points and WLAN routers, item no. 61379 for UK |
| External antenna | AirLancer Extender O-30 2.4 GHz outdoor antenna, item no. 60478 |
| External antenna | AirLancer Extender O-70 2.4 GHz outdoor antenna, item no. 60469 |
| External antenna | AirLancer Extender O-9a 5 GHz outdoor antenna, item no. 61220 |
| External antenna | AirLancer Extender O-18a 5 GHz outdoor antenna, item no. 61210 |
| External antenna* | AirLancer Extender O-D80g 2.4 GHz 'dual linear' polarisation diversity outdoor sector antenna, item no. 61221 |
| External antenna* | AirLancer Extender O-D60a 5 GHz 'dual linear' polarisation diversity outdoor sector antenna, item no. 61222 |
| External antenna | AirLancer Extender O-360ag dualband omnidirectional outdoor antenna, item no. 61223 |
| External antenna | AirLancer Extender I-60ag dualband indoor sector antenna, item no. 61214 |
| External antenna | AirLancer Extender I-180 omnidirectional 2.4 GHz indoor antenna, item no. 60914 |
| External antenna* | AirLancer Extender O-D9a 5 GHz 'dual linear' polarisation diversity outdoor antenna, item no. 61224 |
| Antenna cable | AirLancer cable NJ-NP 3m antenna cable extension, item no. 61230 |

| Accessories | |
|--------------------------------|---|
| Antenna cable | AirLancer cable NJ-NP 6m antenna cable extension, item no. 61231 |
| Antenna cable | AirLancer cable NJ-NP 9m antenna cable extension, item no. 61232 |
| Surge arrester (antenna cable) | AirLancer Extender SA-5L surge arrester (2.4 and 5 GHz), item no. 61553 |
| Surge arrester (LAN cable) | AirLancer Extender SA-LAN surge arrester (LAN cable), item no. 61213 |
| Documentation | LANCOM LCOS Reference Manual (DE), item no. 61700 |
| 19" Rack Mount | 19" rackmount adapter, item no. 61501 |
| Modem Backup | LANCOM Modem Adapter Kit, item no. 61500 |
| VPN Client Software | LANCOM Advanced VPN Client for Windows XP, Windows Vista, Windows 7, single license, item no. 61600 |
| VPN Client Software | LANCOM Advanced VPN Client for Windows XP, Windows Vista, Windows 7, 10 licenses, item no. 61601 |
| VPN Client Software | LANCOM Advanced VPN Client for Windows XP, Windows Vista, Windows 7, 25 licenses, item no. 61602 |
| *) Note | The Polarization Diversity antennas require 2 cables and surge arrestors |
| Item numbers | |
| LANCOM 1821n Wireless (EU) | 61380 |
| LANCOM 1821n Wireless (UK) | 61381 |

LANCOM, LANCOM Systems and LCOS are registered trademarks. All other names or descriptions used may be trademarks or registered trademarks of their owners. Subject to change without notice. No liability for technical errors and/or omissions. 01/10